



R&D 50 Hz GPS CAN sensor

Our CAN-based GPS/GNSS sensor provides accurate positioning with update rates up to 50 Hz (optimal at 40 Hz). It outputs date, time, latitude, longitude, altitude, course, and speed.

Configurable plugin in ODOS dashboard to be added to any ODOS data logger unit, compact and lightweight.

SPECIFICATIONS

| | | |
|---|--------------------------------------|----------------|
| Position accuracy | CEP (50%) | 2.5 m |
| Acquisition | Cold starts | 29 s |
| | Aided starts | 28 s |
| | Reacquisition | 1 s |
| | Max Update Rate | 250 Hz |
| Number of concurrent GNSS | GPS/QZSS L1 C/A + SBAS | |
| Position/COG/Speed Update Rate | 1/2/4/5/10/20/25/40 (default)/ 50 Hz | |
| Environment | Operating temp | -40 to + 80 °C |
| | IP-rating | IP6X |
| Mechanical Shock (Max values) | Duration < 200µs | 10000 g |
| | Duration < 1ms | 2000 g |
| | Free Fall Distance | 1.8 m |

| | | |
|-------------------|-----------------------|--|
| Weight | 30 grams | |
| Dimensions | H 22 x W 40 x L 45 mm | |
| CAN *1 | Baud rates | 1000, 500, 250 kbps |
| | Address Range *2 | 1 (0x01) to 2042 (0x7FA). Default = 0x31E |
| Power | Voltage Range | 9 – 16 V |
| | Current (sleep) | 110 (10 mA) @ 12 V |
| Input pins | 2-28 V | |

*1 The default settings are 1000kbps and start address 0x31E, the unit has no CAN termination.

*2 The unit uses 4 CAN address which are in consecutive order from address that the unit is set to.